
AS18- Dual Digital with Auto Off Timer

Instruction Manual



DESCRIPTION

The AS18 Controller is designed to switch two 240 Vac appliances with a maximum combined current rating of 10 Amps 2400 watts on and off from the spa-side air Switch. It also incorporates a “Time Out” function that can be set for automatically turning the connected appliance[s] off after a pre set time of 10, 20 or 30 minutes.

INSTRUCTIONS

The Air Switch [purchased separately] connects to the air receptacle using air tube [Supplied].

For control of each appliance, press the appropriate switch to turn on and off the connected appliances.

Setting the "Time Out" function:

To set the "Time Out" function, firstly **UNPLUG THE CONTROL BOX FROM THE MAINS POWER SUPPLY**. Open the AS18 Control box. On the inside of the lid, there is Red "Dip" Switch labelled "A". By adjusting the two switches you can adjust the Run Time setting to either "Off, 10 Minutes, 20 minutes or 30 minutes". The time out will control Auxiliary 1 only. If both Auxiliaries are to be controlled move Jumper Pin "B" to the Left Hand Side. Once set, refit the lid ensuring the ribbon cable is connected to both the lid and the main circuit board. Reconnect the AS18 Controller to the mains power supply. Ensure your air switches are plugged into the air switch sockets and your appliances are plugged into the Power Outlets on the AS18 Control Box.

Your AS18 Controller is now ready to use.

WARRANTY-AS18 DUAL DIGITAL WITH AUTO OFF TIMER CONTROLLER

This range of product is covered by a limited 2 year warranty against component failure or faulty workmanship from the date of installation.

A faulty unit should be returned in the first instance to the dealer from which the unit was purchased.

Damage to the unit due to misuse, power surges, lightning strikes or installation that is not in accordance with the manufacturer's instruction may void the warranty.

Warranty does not cover travel costs to or from installation site.

If the power cord is damaged, do not use the controller; return the unit to the supplier for repair.

CUSTOMER RECORD [To be retained by the customer]

DEALER/INSTALLER NAME

SERIAL NUMBER

DATE INSTALLED



Dontek Electronics Pty Ltd

PO Box 239, Bayswater VIC 3153 Australia

Phone: +613 9762 8800 Email: sales@dontek.com.au